

BDX 68 A		Si-P-Darl+Di	=BDX 68: 80/80V	23a	TO-3				MJ 11013, 2SB694
BDX 68 B		Si-P-Darl+Di	=BDX 68: 100/100V	23a	TO-3				MJ 11015, 2SB694
BDX 68 C		Si-P-Darl+Di	=BDX 68: 120/120V	23a	TO-3				MJ 11015
BDX 69	Phi	Si-N-Darl+Di	P, 80/60V, 25/40A, 200W, hFE>1000	(BDX68)	23a	TO-3			MJ 11012, 2SD730
BDX 69 A		Si-N-Darl+Di	=BDX 69: 100/80V	23a	TO-3				MJ 11014, 2SD730
BDX 69 B		Si-N-Darl+Di	=BDX 69: 120/100V	23a	TO-3				MJ 11016, 2SD730
BDX 69 C		Si-N-Darl+Di	=BDX 69: 140/120V	23a	TO-3				MJ 11016
BDX 70	Rca,Sgs	Si-N	LFS P, 70/60V, 10A, 75W, >0,8MHz, (=2N6098)	17j	TO-220	BD 809	17j		BD 709, BD 743A, BD 807, BD 909
BDX 71	Rca,Sgs	Si-N	=BDX 70: (=2N6099)	17j	TO-220	BD 809	17j		BD 709, BD 743B, BD 807, BD 909
BDX 72	Rca,Sgs	Si-N	=BDX 70: 80/70, (=2N6100)	17j	TO-220	BD 809	17j		BD 709, BD 743B, BD 809, BD 909
BDX 73	Rca,Sgs	Si-N	=BDX 72: (=2N6101)	17j	TO-220	BD 809	17j		BD 709, BD 743B, BD 809, BD 909
BDX 74	Rca,Sgs	Si-N	=BDX 70: 45/40V, 16A, (=2N6102)	17j	TO-220	BD 809	17j		BD 743, BD 905, BDT 81
BDX 75	Rca,Sgs	Si-N	=BDX 74: (=2N6103)	17j	TO-220	BD 809	17j		BD 743, BD 905, BDT 81
BDX 77	Phi	Si-N	LFS P, 100/80V, 8/12A, 60W, >7MHz	(BDX78)	17j	TO-220	BD 809	17j	BD 543C, BD 711, BD 801, 2SD866
BDX 77 F		Si-N	=BDX 77: Iso, >20W	17c	SOT-186	2SD1411	17c		BDT 95F, 2SD1411, 2SD1588, 2SD1833
BDX 78	Phi	Si-P	LFS P, 80/80V, 8/12A, 60W, >7MHz	(BDX77)	17j	TO-220	BD 810	17j	BD 544B, BD 710, BD 800, BD 810
BDX 78 F		Si-P	=BDX 78: Iso, >20W	17c	SOT-186	2SB1018	17c		BDT 96F, 2SB1018, 2SB1290, 2SA1396
BDX 83	Rca	Si-N-Darl+Di	P, 40/40V, 10/15A, 125W, >20MHz, hFE>1000	(BDX84)	23a	TO-3	BDW 83 C	18j	BDW 83, BDX 85, BDX 87, MJ 3000, 2N6057
BDX 83 A		Si-N-Darl+Di	=BDX 83: 60/60V	23a	TO-3	BDW 83 C	18j		BDW83A, BDX85A, BDX87A, MJ3000, 2N6057
BDX 83 B		Si-N-Darl+Di	=BDX 83: 80/80V	23a	TO-3	BDW 83 C	18j		BDW83B, BDX85B, BDX87B, MJ3001, 2N6058
BDX 83 C		Si-N-Darl+Di	=BDX 83: 100/100V	23a	TO-3	BDW 83 C	18j		BDW83C, BDX85C, BDX87C, 2N6059, 2SD628++
BDX 84	Rca	Si-P-Darl+Di	P, 40/40V, 10/15A, 125W, >20MHz, hFE>1000	(BDX83)	23a	TO-3	BDW 84 C	18j	BDW 84, BDX 86, BDX 88, MJ 2500, 2N6050
BDX 84 A		Si-P-Darl+Di	=BDX 84: 60/60V	23a	TO-3	BDW 84 C	18j		BDW84A, BDX86A, BDX88A, MJ2500, 2N6050
BDX 84 B		Si-P-Darl+Di	=BDX 84: 80/80V	23a	TO-3	BDW 84 C	18j		BDW84B, BDX86B, BDX88B, MJ2501, 2N6051
BDX 84 C		Si-P-Darl+Di	=BDX 84: 100/100V	23a	TO-3	BDW 84 C	18j		BDW84C, BDX86C, BDX88C, 2N6052, 2SB638++
BDX 85	Sgs	Si-N-Darl+Di	P, 45/45V, 10/15A, 100W, 10MHz, hFE>1000	(BDX86)	23a	TO-3	BDW 83 C	18j	BDW 83, BDX 83A, BDX 87, MJ 3000, 2N6057
BDX 85 A		Si-N-Darl+Di	=BDX 85: 60/60V	23a	TO-3	BDW 83 C	18j		BDW83A, BDX83A, BDX87A, MJ3000, 2N6057
BDX 85 B		Si-N-Darl+Di	=BDX 85: 80/80V	23a	TO-3	BDW 83 C	18j		BDW83B, BDX83B, BDX87B, MJ3001, 2N6058
BDX 85 C		Si-N-Darl+Di	=BDX 85: 100/100V	23a	TO-3	BDW 83 C	18j		BDW83C, BDX83C, BDX87C, 2N6059, 2SD628++
BDX 86	Sgs	Si-P-Darl+Di	P, 45/45V, 10/15A, 100W, 10MHz, hFE>1000	(BDX85)	23a	TO-3	BDW 84 C	18j	BDW 84, BDX 84A, BDX 88, MJ 2500, 2N6050
BDX 86 A		Si-P-Darl+Di	=BDX 86: 60/60V	23a	TO-3	BDW 84 C	18j		BDW84A, BDX84A, BDX88A, MJ2500, 2N6050
BDX 86 B		Si-P-Darl+Di	=BDX 86: 80/80V	23a	TO-3	BDW 84 C	18j		BDW84B, BDX84B, BDX88B, MJ2501, 2N6051
BDX 86 C		Si-P-Darl+Di	=BDX 86: 100/100V	23a	TO-3	BDW 84 C	18j		BDW84C, BDX84C, BDX88C, 2N6052, 2SB638++
BDX 87	Sgs	Si-N-Darl+Di	P, 45/45V, 12/18A, 120W, 25MHz, hFE>1000	(BDX88)	23a	TO-3	BDW 83 C	18j	BDW 83, BDX 67, 2N6057, MJ 4033
BDX 87 A		Si-N-Darl+Di	=BDX 87: 60/60V	23a	TO-3	BDW 83 C	18j		BDW 83A, BDX 67, 2N6057, MJ 4033
BDX 87 B		Si-N-Darl+Di	=BDX 87: 80/80V	23a	TO-3	BDW 83 C	18j		BDW 83B, BDX 67A, 2N6058, MJ 4034
BDX 87 C		Si-N-Darl+Di	=BDX 87: 100/100V	23a	TO-3	BDW 83 C	18j		BDW 83C, BDX 67B, 2N6059, MJ 4035
BDX 88	Sgs	Si-P-Darl+Di	P, 45/45V, 12/18A, 120W, 35MHz, hFE>1000	(BDX87)	23a	TO-3	BDW 84 C	18j	BDW 84, BDX 66, 2N6050, MJ 4030
BDX 88 A		Si-P-Darl+Di	=BDX 88: 60/60V	23a	TO-3	BDW 84 C	18j		BDW 84A, BDX 66, 2N6050, MJ 4030
BDX 88 B		Si-P-Darl+Di	=BDX 88: 80/80V	23a	TO-3	BDW 84 C	18j		BDW 84B, BDX 66A, 2N6051, MJ 4031
BDX 88 C		Si-P-Darl+Di	=BDX 88: 100/100V	23a	TO-3	BDW 84 C	18j		BDW 84C, BDX 66B, 2N6052, MJ 4032
BDX 91	Phi	Si-N	LFS P, 60/60V, 8/12A, 90W, >4MHz, <1/2µs	(BDX92)	23a	TO-3	BD 317	23a	BD 245A, BD 311, BDV 91, 2N5873, ++
BDX 92	Phi	Si-P	LFS P, 60/60V, 8/12A, 90W, >4MHz, <1/2µs	(BDX91)	23a	TO-3	BD 318	23a	BD 246A, BD 312, BDV 92, 2N5871
BDX 93	Phi	Si-N	=BDX 91: 80/80V	(BDX94)	23a	TO-3	BD 317	23a	BD 245B, BD 313, BDV 93, 2N5874, ++
BDX 94	Phi	Si-P	=BDX 92: 80/80V	(BDX93)	23a	TO-3	BD 318	23a	BD 246B, BD 314, BDV 94, 2N5872, ++
BDX 95	Phi	Si-N	=BDX 91: 100/100V	(BDX96)	23a	TO-3	BD 317	23a	BD 245C, BDV 95, 2N5632...5633, ++
BDX 96	Phi	Si-P	=BDX 92: 100/100V	(BDX95)	23a	TO-3	BD 318	23a	BD 246C, BDV 96, 2N6229...6230, ++

BDY

BDY 10	Phi	Si-N	LFS P, 50/40V, 2/4A, 150W, >1MHz	23a	TO-3				BD 311, BDW 21A, 2N3055, 2N4914, ++
BDY 11	Phi	Si-N	=BDY 10: 100/70V	23a	TO-3				BD 317, BDW 21C, 2N3055, 2N5632, ++
BDY 12	Sie	Si-N	LFS P, 60/40V, 3A, 26W(Tc=45°), 70MHz, <0,3/1,5µs	22a	SOT-9				BDW 25, BDX 25, BDV 10...12, 2SC3252
BDY 13	Sie	Si-N	=BDY 12: 80/60V	22a	SOT-9				BDW 25, BDX 25, BDV 10...12, 2SC3252
BDY 15	Itt	Si-N	LFS P, 36/36V, 2,5/4A, 11,5W, 100MHz	22a	SOT-9				BDW 25, BDX 25, BDV 10...12, 2SC3252
BDY 16	Itt	Si-N	=BDY 15: 64/64V	22a	SOT-9				BDW 25, BDX 25, BDV 10...12, 2SC3252
BDY 17	Phi	Si-N	LFS P, 80/60V, 10/25A, 115W, 1MHz	23a	TO-3	2SD1047	18j		BD 745B, BD 313, BDW 21B, 2N3055, ++
BDY 18	Phi	Si-N	=BDY 17: 120/70V	23a	TO-3	2SD1047	18j		BD745D, BDW10, 2N5633, 2SC2706, 2SD1047+
BDY 19	Phi	Si-N	=BDY 17: 150/80V	23a	TO-3	2SD1047	18j		BD745E, BDW12, 2N3442, 2SC2706, 2SD1047+
BDY 20	Phi	Si-N	LFS P, 100/60V, 15A, 117W, 1MHz, (=2N3055)	23a	TO-3	2N3055	23a		BD 317, BD 745C, BDW 51C, 2N3055, ++
BDY 21	Sie	Si-N	LFS P, 80/60V, 3A, 25W(Tc=45°), >30MHz, <300/-ns	22a/3Pin	SOT-9a				BDW 25, BDX 25, BDV 10...12, 2SC3252
BDY 22	Sie	Si-N	=BDY 21: 100/80V	22a/3Pin	SOT-9a				BDW 25, BDX 25, BDV 10...12, 2SC3252
BDY 23	Tho	Si-N	LFS P, 60/60V, 6A, 87,5W, >10MHz, <0,5/2µs	23a	TO-3				BD 245A, BD 311, BDW 21A, 2N3055, ++
BDY 24	Tho	Si-N	=BDY 23: 100/90V	23a	TO-3				BD 245C, BD 317, BDW 21C, 2N3055, ++
BDY 25	Tho	Si-N	=BDY 23: 200/140V	23a	TO-3	MJ 15015	23a		BD245F, BDW16, MJ15015, 2SC1585, 2SC2608
BDY 26	Tho	Si-N	=BDY 23: 300/180V	23a	TO-3				BUX 18, BUY 18, BUY 35, BUY 67, ++
BDY 27	Tho	Si-N	=BDY 23: 400/200V	23a	TO-3				BUX 18B, BUY 18S, BUY 67, BUY 77, ++
BDY 28	Tho	Si-N	=BDY 23: 500/250V	23a	TO-3				BUW 34, BUX 15, BUX 45, BUY 69...70C ++
BDY 29	Rca	Si-N	LFS P, 100/75V, 30/30A, 220W, >0,2MHz	23a	TO-3				BDW 30, BDV 57, MJ 802, 2SD797
BDY 34	Aeg	Si-N	LFS P, 45/40V, 3A, 21W, >80MHz, <0,5/1µs	14h	TO-126	2SD1348	14h		BD 785, MJE 240...242, 2SD1348
BDY 34	Aeg	Si-N	LFS P, 45/40V, 3A, 13W(Tc=45°), >80MHz, <0,5/1µs	22a	TO-66				BDV 10...12, BDW 25, BDX 25, 2SC3252, ++
BDY 37	Rca	Si-N	LFS P, 160/140V, 16/30A, 150W, >0,2MHz	23a	TO-3	MJ 15015	23a		BDW 32, BDW 34, BDW 36, BDV 58, 2N3773
BDY 37 A		Si-N	=BDY 37: 250W	23a	TO-3				BDW 32, BDW 34, BDW 36, 2SC2608
BDY 38	Phi	Si-N	LFS P, 50/40V, 6A, 117W, 1MHz	23a	TO-3	2N3055	23a		BD 311, BD 745A, BDW 21A, 2N3055, ++
BDY 39	Sgs, Sie	Si-N	LFS P, 100/60V, 15/22A, 117W, 1,1MHz	23a	TO-3	2N3055	23a		BD 317, BD 745C, BDW 51C, 2N3055, ++
BDY 42	Aeg	Si-N	S P, 400/250V, 5/10A, 60W, 12MHz, <55/4000ns	23a	TO-3				BUW 71, BUX 18B, BUY 18S, BUY 67, ++
BDY 43	Aeg	Si-N	=BDY 42: 600/300V	23a	TO-3				BUS 11, BUW 25, BUW 82, BUY 78...79, ++
BDY 44	Aeg	Si-N	=BDY 42: 750/350V	23a	TO-3				BUS 11, BUW 26, BUX 82, BUY 79, ++
BDY 45	Aeg	Si-N	S P, 400/250V, 15/17A, 95W, 13MHz, <0,5/3,5µs	23a	TO-3				BUW 44, BUX 13, BUX 25, BUY 50, ++
BDY 46	Aeg	Si-N	=BDY 45: 600/300V	23a	TO-3				BUS 13, BUW 45...46, BUX 48, 2SD641
BDY 47	Aeg	Si-N	=BDY 45: 750/350V	23a	TO-3				BUS 13, BUW 45...46, BUX 48, 2SC3094
BDY 48/200	Aeg	Si-N	S P, 200V, 3,5A, 100W, 5MHz	23a	TO-3				BUX 16...18, BUY 18, BUY 35, BUY 67, ++
BDY 48/300	Aeg	Si-N	=BDY 48/200: 300V	23a	TO-3				BUX 16A...18A, BUY 18, BUY 35, BUY 67, ++
BDY 48/400	Aeg	Si-N	=BDY 48/200: 400V	23a	TO-3				BUX 16C...18C, BUY 18S, BUY 67, ++
BDY 49	Aeg	Si-N	S P, /100V, 30A, 150W	23a	TO-3				BDW 30, BDV 29, BDV 57, MJ 802, 2SD797
BDY 53	Tho	Si-N	LFS P, 100/60V, 12A, 60W, >20MHz	23a	TO-3				BD 317, BD 745C, BDW 51C, 2N3055, ++
BDY 54	Tho	Si-N	=BDY 53: 180/120V	23a	TO-3				BDW 14, BDW 16, BDV 54, BDV 56, ++
BDY 55	Rca, Tho	Si-N	LFS P, 100/60V, 15A, 115W, >10MHz, <0,5/2µs	23a	TO-3	2N3055	23a		BD 317, BD 745C, BDW 51C, 2N3055, ++
BDY 56	Rca, Tho	Si-N	=BDY 55: 180/120V	23a	TO-3	MJ 15015	23a		BDW 14, BDW 16, BDV 56, 2SC2607, ++
BDY 57(A)	Rca, Tho	Si-N	LFS P, 120/80V, 25A, 175W, >7MHz, <1/2µs	23a	TO-3				BDW 30, 2N6032, 2N6274...6275
BDY 58	Rca, Tho	Si-N	=BDY 57: 160/125V	23a	TO-3				BDW 32, BDW 34, 2N6276...6277
BDY 58 R	Rca	Si-N	=BDY 57: 250/160V	23a	TO-3				BUW 11...12, BUX 11...12, BUW 58, BUW 73
BDY 60	Phi	Si-N	LFS P, 120/60V, 5/10A, 15W(Tc=100°), 100MHz	23a	TO-3				BDV 90, 2SC2681, 2SC2706, 2SC2837
BDY 61	Phi	Si-N	=BDY 60: 100/60V	23a	TO-3				BDV 90...91, 2SC2681, 2SC2706, 2SC2837